



**Product Overview:**

LA-113 RG-8 50 Ohm Coaxial Cable is measured and cut per foot. It is best used when more distance is needed for the antennas to have better coverage. Recommended for coaxial runs more than 100 ft. (30.5 m) at 72 MHz or 50 ft. (15.24 m) at 216 MHz. The LA-113 minimum order is 20 ft. (6.1 m). LA-113 will give you better distance with lower loss of signal power. Signal loss for 72 MHz is 1 dB per 50 ft. Signal loss for 216 MHz is 2 dB per 50 ft.

**Highlights:**

- Furthers antenna location
- Longest runs with little signal loss
- Cut to custom length with no connectors

**Includes:**

LA-113 RG-8 50 Ohm Coaxial Cable (Per ft.) (minimum of 20 ft.)

Product Specification: RG-8 50 Ohm Low-Loss Coaxial Cable (Per ft.)	
<b>RF</b>	
Frequency Range	72.0250-75.9500 MHz & 216.0125-216.9875 MHz
<b>Physical</b>	
Material	Foam Polyethylene Insulation, PVC Jacket, bare copper conductor, bare copper braided shield
Shipping Weight	15.0 lbs. (6.8 kg) per 100 ft.
Diameter	Outer: .403 in. (10.24 mm), Inner: .285 in. (7.24 mm)
Unit Weight	14.2 lbs. (6.5 kg) per 100 ft.