



Broadcast Quality Made Affordable

PTZOptics

Introducing the new SuperJoy Joystick Controller supporting Network and Serial Camera Control. Experience the full capabilities by pairing it with PTZOptics or HuddleCamHD cameras.

Main Features

- Durable metal housing
- PTZOptics VISCA over IP & Serial control
- Limited NDI & Sony control
- PTZOptics Camera On Screen Display control
- Full Pan / Tilt / Zoom camera control
- PTZ, Focus, and Preset Speed Adjustment on the fly
- 4 Camera Control Groups
 - 7 Cameras per Camera Group
- 255 camera presets, 9 Quick presets
- 4 Customizable buttons (TCP, UDP, & HTTP)
- Fine tune zoom & focus control dials
- Buttons glow / flash when available
- RTSP Decoder via HDMI
- PTZOptics Focus Lock & Unlock
- Large LCD screen with controller status
- Import / Export settings via network & USB
- 2-Year warranty

Model Number: PT-SUPERJOY-G1

What's in the box?

- PT-SUPERJOY-G1 Joystick Controller
- 12V 2A DC International Power Supply
- RS-232C | DB9 to 8-pin mini-din cable
- PT-SUPERJOY-G1 Quick Start Guide



Technical Specifications

Connections	RS-232, RS-485, RS-422, RJ-45
Control Protocols	VISCA, VISCA over IP, PELCO-D, PELCO-P, Sony, & NDI
Max Cameras	28 cameras total (4 groups of 7 channels)
Recommended Max Distance	RS-232 / RS-422: 50 ft 15m RS-485: 3,937 ft 1200m Ethernet: 328 ft 100m
Baud rate	1200 ~ 19200 bps

Operation Specifications

Power	6W 12VDC / PoE (802.3af) (Only use one (1) power source at a time.)
Working Temp	14° F ~ 122° F -10° C ~ +50° C
Working Humidity	10% ~ 90% (non-condensation)
Weight	3.75 lbs 1.70 kg
Dimensions (in.)	13.94 W x 7.05 D x 3.98 H
Dimensions (mm.)	370 W x 180 D x 101 H